

正面



真无线立体声  
无线蓝牙耳机

产品规格


蓝牙版本:	V5.1+EDR
支持协议:	A2DP1.3/HFP1.6/HSP1.2
电源电压:	5V
充电时间:	1小时
传输范围:	10-15米
耳机电池容量:	30毫安
待机时间:	240小时
播放/通话时间:	2-2.5小时
充电仓电池容量:	200毫安
耳机尺寸:	20*15*25mm
充电仓尺寸:	66mm*31.3mm

产品规格

充电电流:	耳机30mAh 充电仓300mAh
蓝牙 Profile:	a2dp,avctp,avdtp,avrcp,hfp,sgp, smp,atf,gap,gatt,rfcomm,adp,blecap
蓝牙解码方式:	1M GFSK,2M GFSK,S2 CODE\ S8 CODE\= /4 DQPSK a
RF载波频率:	2.4G
充电盒充电时间:	1.5-2H
充电盒给耳机充电次数:	3次
TWS连接成功指示:	主副机蓝灯间隔慢闪
喇叭型号:	φ13.Round horn
喇叭尺寸:	φ13mm
耳机重量:	7.0g
充电仓重量:	39.0g

产品规格

喇叭阻抗:	32Ω
喇叭额定功率:	3mW
喇叭最大功率:	5mW
喇叭频率响应:	20hz-20Khz
喇叭灵敏度:	105db±3db/1khz
耳机电池:	440911 (30mah) (KC.Y3440911.3.7V.30mah)
充电仓电池:	601230 (200mAh) (KC.Y2601230.3.7V.200mah)
蓝牙芯片:	蓝讯5376
外壳材质:	ABS+PC



产品操作指南


- Ⓞ 长按多功能键4s左右/放回充电仓, 充电关机
- Ⓞ 长按多功能键5s/从充电仓取出, 自动开机
- Ⓞ 左右耳配对, 开机自动配对, 不分左右
- 🔊 音量加/减, 音乐播放状态下, 双击左/右耳
- ⏸ 单击播放或暂停
- ⏪ 三击左侧上一曲
- ⏩ 三击右侧下一曲
- 🗣 长按多功能键2秒钟启用Siri
- 📞 当有来电时, 双击接听或挂断电话。
- 🔌 按住3秒钟拒接来电。
- 🔋 充满电充电仓显示100 耳机红灯自动熄灭

产品操作指南

- 手机蓝牙界面蓝牙名称: Air-S4, 呼吸灯蓝灯
- 配对成功, 正常操作: 播歌、打电话, 呼吸灯蓝灯
- 5分钟内无连接耳机关机
- 机器关机后重启, 蓝牙自动连接已配对过的设备, 回连失败进入配对模式
- L为左声道, R为右声道芯片不区分L/R
- 来电, 英文报号
- 充电时耳机关机, 红灯长亮
- 耳机电量低, 红灯呼吸灯报语音提示
- 苹果手机电量同步显示
- 充满电充电仓显示100 耳机红灯自动熄灭

本产品可与您的所有设备一起使用

支持以下设备



警告

1. 耳机应该存放于干燥环境中, 以避免油, 水, 潮湿和灰尘对产品性能造成影响。
2. 避免使用刺激性液体, 有机溶剂或包含以上成分的物品清洁耳机。
3. 请在各项功能参数规定的范围之内使用耳机, 并注意耳机对环境的影响, 请确保耳机和手机的距离在10米以内, 以便顺畅的进行连接。
4. 如果连接失败或者连接不稳定, 请勿自行拆开耳机或耳机配件, 我们对人为错误造成的故障不承担责任。
5. 关于充电, 请使用标准USB线缆或我们指定的线缆对耳机进行充电。
6. 日常使用中, 请保持您的耳机电量充足。

反面



TWS  
Wireless stereo headset

Specitication:

Bluetooth version:	V5.0+EDR
Bluetooth protocol	A2DP1.3/HFP1.6/HSP1.2
Voltage:	5V
Charging time:	1H
Charging time of charging box:	10m-15m
earphone capacity	30mAh
Standby time:	240Hs
Play/Calling Time:	2-2.5Hs
Charging box capacity:	200mAh
Headphone size:	20*15*25mm
Charging box size:	66mm*31.3mm

Specitication:

recharging current:	headset50mAh Charging case300mAh
Bluetooth Profile:	a2dp,avctp,avdtp,avrcp,hfp,sgp, smp,atf,gap,gatt,rfcomm,adp,blecap
Bluetooth decoding method:	1M GFSK,2M GFSK,S2 CODE\ S8 CODE\= /4 DQPSK a
Carrier frequency:	2.4G
Charging time of charging box:	1.5-2H
The number of times the charging box charges the headset:	3 times
TWS connection success indication:	The blue lights of main and auxiliary engines flash slowly at intervals
speaker model:	φ13.Round horn
speaker size:	φ13mm
Headphone weight:	7.0g
Charging compartment weight:	39.0g

Specitication:

Impedance:	32Ω
Rated power:	3mW
Maximum power	5mW
Frequency response:	20hz-20Khz
Sensitivity:	105db±3db/1khz
Headset battery:	440911 (30mah) (KC.Y3440911.3.7V.30mah)
Rechargeable battery:	601230 (300mAh) (KC.Y2601230.3.7V.200mah)
Chipset:	Bluetrum 5376
Shell material:	ABS+PC



Product operation instructions

- Ⓞ Long press for about 4s / put it back into the charging compartment, charging and shutting down
- Ⓞ Press and hold the multi-function button for 5s, automatically turn on.
- Ⓞ Automatically pair at boot, regardless of left or right
- 🔊 Volume up/down, double-click the left/right ear
- ⏸ Double press to play or pause.
- ⏪ Triple press left to skip back.
- ⏩ Triple press right to skip forward.
- 🗣 Long press for 2 seconds to enable Siri
- 📞 Double press to answer incoming call or hang up, press and hold 3 seconds to reject call.
- 🔋 Fully charged, the charging compartment shows 100, the red light of the headset is automatically turned off

Product operation instructions

- After the left and right ears are paired, the Bluetooth name can be searched in the Bluetooth interface of the mobile phone: Air-S4
- Normal operation: operations such as playing songs and making calls
- Power off without connecting headphones within 5 minutes
- After the machine is shut down and restarted, the Bluetooth will automatically connect to the paired devices, and the pairing mode will enter when the connection fails.
- L is the left channel, R is the right channel. The chip does not distinguish L/R
- English newspaper number
- The headset turns off while charging
- Red light breathing light voice prompt
- Sync display of iPhone battery
- After the earphone is fully charged, the digital display of the charging chamber shows 100, and the red light of the earphone goes out automatically

Use with all your devices:

Support the following devices



Precautions

1. The earphones should be stored in a dry environment, to avoid oil, water, moisture and dust from affecting product performance.
2. Avoid using stimulus, organic solvents or items containing these ingredients to clean the earphone.
3. The use of earphones should be correct as per the specification, pay attention to the influence of environment on the earphones.In order to ensure the smooth connection, please keep the distance between the earphones and phones within 10 meters.
4. If the earphones are failed to connect or with poor connection, please do not take apart the earphones or the accessories on your own. Please note it that we are not responsible for man made mistake.
5. Regarding charging earphones, please use the standard USB cable or pointed charging cable from us to charge the earbuds.
6. Please keep your earbuds battery fresh for normal use.